

**Ref: FAQ0196****Version: 1.0****Title-Multilog & LX remote call in change****Made By: AB 17/09/15****(Issue 2)**

Remotely changing the call in time of an SMS Multilog or LX logger

To change the call-in time of a logger remotely, you need to send the logger an SMS message from your mobile phone.

The message is Prog1 followed by the phone number it is to send messages to, followed by a comma and then the hour it is to send (in 24hr format), followed by a hash ('#')

e.g., for a logger to send messages to Datagate at 7.00am, you would need to send the following message:

Prog1+447786200833,07#

This will update the telephone number and call-in time during the logger's next power window. You will receive an SMS message back to your phone with confirmation of the new call-in time.

The command which will be sent is asking the logger to call in at 07:00 GMT. Note that you cannot allocate the minutes for the logger to send messages, this is allocated within the logger to prevent all loggers dialing at the same time.

Document History:

Edition	Date of Issue	Modification	Notes
1st		Release	
2nd	17/09/15	Format update	